

KINGDOM ELECTRONICS CC

Electronic Design and Manufacture Security & Access Control Equipment

PO Box 1940 • HONEYDEW • 2040 Tel: (011) 791 1362/3749 • Fax: (011) 791 6610

E-mail: ke-sa@mweb.co.za Website: www.kesa.co.za

TECHNICAL PRODUCT BULLETIN

2zone alarm pc board

Application


Complete alarm controller for small home, caravan or outbuilding.

Specifications

- 16v AC input, 12v DC operation.
- Built in 1A battery charging circuit.
- 12v DC fused output.
- Key switch input for arm/disarm.
- Status LED output.
- 2 zone inputs, 1 panic input, 1 minute timed siren output.
- Physical size: 120mm x 60mm.

Wiring Diagram

Keysw is + pulse type trigger Panic is + pulse trigger Zone 1 and 2 are N.C. inputs



Installation

- Connect 16v AC, 12v DC to equipment and battery leads.
- Pulse keysw input, if zones are set the system will arm, status LED on.
- Status LED will flash indicating which zone is open, ie 1 or 2 flashes.
- Trigger a zone and siren will sound for 1 minute or until reset via the keysw.